

# SHARP®

**ELECTRONIC CASH REGISTER  
CAISSE ENREGISTREUSE ELECTRONIQUE**

MODEL  
MODELE **ER-A320**

**INSTRUCTION MANUAL**

**MANUEL D'INSTRUCTIONS**



**CAUTION**

The socket-outlet shall be installed near the equipment and shall be easily accessible.

**ATTENTION**

La prise de courant murale devra être installée à proximité de l'équipement et être facilement accessible.

---

# INTRODUCTION

Thank you very much for your purchase of the SHARP Electronic Cash Register, Model ER-A320. Please read this manual carefully before operating your machine in order to gain a full understanding of its functions and features. Please keep this manual for future reference. It will help you if you encounter any operational problems.

---

## IMPORTANT

- **Install your cash register in a location that is not subject to direct radiation, unusual temperature changes, or high humidity or exposed to water sources.**  
Installation in such locations could cause damage to the cabinet and the electrical components:
- **The register should not be operated by an individual with wet hands.**  
The water could seep into the interior of the register and cause component failure.
- **When cleaning your register, use a dry, soft cloth. Never use solvents, such as benzine and thinner.**  
The use of such chemicals will lead to discoloration or deterioration of the cabinet.
- **The register plugs into any standard wall outlet (local voltage  $\pm 10\%$  AC).**  
Other electrical devices on the same electrical circuit could cause the register to malfunction.
- **If the register malfunctions, call your local dealer for service - do not try to repair the register yourself.**
- **For a complete electrical disconnection, pull out the mains plug.**

---

## PRECAUTION

This Electronic Cash Register has a built-in memory protection circuit which is operated by a rechargeable battery pack.

It should be known that all batteries will, in time, dissipate their charge even if not used. Therefore to insure an adequate initial charge in the protection circuit and to prevent any possible loss of memory upon installation, it is recommended that each unit be allowed to be recharged for a period of 24 to 48 hours prior to use by the customer.

In order to charge the battery pack, the machine must be plugged in and its power switch must be set to the "ON" position. This recharging precaution can prevent unnecessary initial service calls.

---

# CONTENTS

INTRODUCTION .....	1
IMPORTANT .....	1
PRECAUTION .....	1
EXTERNAL VIEW .....	6
Front view .....	6
Rear view .....	6
Drawer lock key .....	6
KEYBOARD .....	7
Standard keys .....	7
Optional keys .....	8
MODE SWITCH AND MODE KEYS .....	8
DISPLAYS .....	9
Machine state symbols .....	9
BEFORE OPERATING THE CASH REGISTER .....	10
1. Installing the cash register .....	10
2. Preparing the paper roll and the ink roller .....	10
<b>FOR THE OPERATOR</b>	
PRIOR TO ENTRIES .....	12
1. Preparations for entries .....	12
Receipt and journal paper rolls .....	12
2. Error warning .....	12
Error escape function .....	12
ENTRIES .....	13
1. Item entries .....	13
Single item entries .....	13
Repeat entries .....	14
Multiplication entries .....	15
Split-pricing entries .....	16
Single item cash sale (SICS) entries .....	17
2. Display of subtotals .....	17
Merchandise subtotal .....	17
Taxable subtotal .....	17
Including-tax subtotal (full subtotal) .....	17
3. Finalization of transaction .....	18
Cash or check tendering .....	18
Mixed tendering (check + cash) .....	18
Cash or check sale that does not need any tender entry .....	19
Charge (credit) sale .....	19
Mixed-tender sale (cash or check tendering + charge tendering) .....	19
4. Tax calculations .....	20
Automatic tax .....	20
Manual tax .....	20
Automatic-tax delete .....	20
Tax status shift .....	21
5. Auxiliary entries .....	21
Percent calculations (premium or discount) .....	21
Discount entries .....	22
Refund entries .....	23
Printing of non-add code numbers .....	23

6. Payment treatment .....	24
Currency conversion .....	24
Received on account entries .....	24
Paid out entries .....	25
No sale (exchange) .....	25
Cashing a check .....	25
7. Automatic sequencing key (AUTO) entries .....	25
<b>CALCULATION MODE</b> .....	26
Basic calculations .....	26
Using the memory key .....	26
<b>CORRECTION</b> .....	27
1. Correction of the last entry (direct void) .....	27
2. Correction of the next-to-last or earlier entries (indirect void) .....	27
3. Subtotal void .....	28
4. Correction of incorrect entries not handled by the direct or indirect void function .....	28
<b>CORRECTION AFTER FINALIZING A TRANSACTION</b> .....	29
<b>OVERRIDE ENTRIES</b> .....	29
<b>SPECIAL PRINTING FUNCTIONS</b> .....	30
1. Receipt issuance after finalization .....	30
2. Validation printing function .....	30
Validation slip setting and printing .....	30
Validation printing examples .....	31
Validation slip specification .....	32
3. Printing of the employee arrival and departure times .....	32

<b>FOR THE MANAGER</b>
------------------------

<b>PROGRAMMING</b> .....	33
<b>Direct Programming</b> .....	33
1. Setting the date, time, and consecutive number .....	33
Date .....	33
Time .....	33
Consecutive number .....	34
2. Programming for departments .....	34
Unit price .....	34
Functional selection .....	35
3. Price lookup (PLU) programming .....	37
Unit price .....	37
Functional selection .....	37
PLU assignment to departments .....	39
4. Programming for discount keys .....	40
Discount amount (⊖) .....	40
High amount lockout (HALO) and tax status (⊖) .....	41
5. Programming for percent keys .....	42
Percent rate (%) .....	42
Sign (+/-) and tax status (%) .....	42
6. Programming for conversion keys .....	43
Currency conversion rate (CONV) .....	43
7. Programming for the CA2, RA, PO, CH, CHK, and TAX keys .....	43
High amount lockout (HALO) (CA2, RA, PO, CH, CHK, and TAX) .....	43
<b>Job-Code-Based Programming</b> .....	44
1. Setting the date and time .....	44
Date (#2610, Direct) .....	44
Time (#2611, Direct) .....	44

2. Setting the register and consecutive numbers .....	44
Register number (#2612) .....	44
Consecutive number (#2613, Direct) .....	44
3. Programming for the automatic tax calculation function .....	45
Tax table (applicable to the add-on tax)(#2710) .....	45
Tax rate (#2711) .....	46
4. Programming for departments .....	46
Unit price (#1110, Direct) .....	46
Functional selection 1 (#2111, Direct) .....	47
Limit amount (HALO) (#2112, Direct) .....	47
Functional selection 2 (#2110) .....	47
Group number (#2116) .....	48
5. Price lookup (PLU) programming .....	48
PLU assignment to departments (#1200, Direct) .....	48
Unit price (#1210, Direct) .....	48
Functional selection (#2210, Direct) .....	49
6. Programming for the miscellaneous keys .....	49
Rate and discount amount (%, CONV, and ⊖) (#1310, Direct) .....	49
Limit amount (HALO) (⊖, TAX, RA, and PO) (#2312, Direct) .....	50
Sign (+/-) and tax status (%, ⊖) (#2311, Direct) .....	50
7. Programming for the media keys .....	50
High amount lockout (HALO) for media keys (#2322, Direct) .....	50
Functional selection (#2320) .....	51
High amount lockout (HALO) for check change, check cashing, and cash in drawer (#2321) .....	51
8. Programming various functions .....	52
Optional feature selection (#2616) .....	52
Setting the time limit for THE TILL TIMER™ (#2617) .....	53
Setting the AUTO key - Automatic sequencing key (#2900) .....	53
9. Activating and deactivating the TRAINING mode .....	54
TRAINING-mode activation/deactivation (#2910, 2911) .....	54
TRAINING-mode operations .....	55
10. Reading stored programs .....	55
Program details and procedures for their reading .....	55
Sample printouts .....	56
<b>READING (X) AND RESETTING (Z) OF SALES TOTALS .....</b>	<b>58</b>
1. Summary of reading (X) and resetting (Z) reports and the key operations to obtain the reports .....	58
2. Daily sales totals .....	59
Full report .....	59
Hourly report .....	61
Full department report .....	61
Individual group report .....	62
PLU report .....	62
PLU by associated department report .....	62
Transaction report .....	62
3. Periodic consolidation .....	63
Full report .....	63
Daily net report .....	63
<b>MAINTENANCE .....</b>	<b>64</b>
1. In case of power failure .....	64
2. In case of printer's motor locking .....	64
3. Installing and removing the paper roll .....	65
Installing the paper roll .....	65

Removing the paper roll .....	65
Removing a paper jam .....	66
Recording paper specifications .....	66
4. Replacing the ink roller .....	67
5. Ink refill .....	68
6. Removing the till and the drawer .....	69
7. Opening the drawer by hand .....	69
8. Before calling for service .....	69
<b>LIST OF OPTIONS</b> .....	<b>70</b>
<b>SPECIFICATIONS</b> .....	<b>71</b>

[Click here to download the full manual at THE-CHECKOUT-TECH.COM](http://THE-CHECKOUT-TECH.COM)